


## Instructions for Tectra Twin Plasma/LCD stand

- 1) Fix the base to the main stand assembly, using the five M8 nuts and washers. (As in picture 1).



- 2) Fix the universal Plasma/LCD wall bracket to the main stand assembly, using the four M6x25 domed screws and spacers. (As in picture 2).



- 3) Fix the left hand and right hand brackets to the back of you Plasma/LCD, using one of the four sizes of studs, nuts and washers provided, these only need to be finger tight when screwed into the back of you screen. When tightening up nuts, make sure the stud does not turn. (As in picture 3). Nylon spacers are optional.



- 4) Hook the screen into position. (As in picture 4).



**Please note maximum weight of screen is 60kg, and 20kg for the shelf.**

- 5) Place the glass shelf into the brackets and tighten screws on the underside. (As in picture 5).



### Notes for A2000 systems


- 1) A2000 to fit M8 nuts into main stand assembly x 5 + washers.
- 2) Fit shelf fixing brackets to the main stand assembly x 2 M4x10 csk screws
- 3) Fit plastic cable tidy's in place x 6.
- 4) Fit rubber feet x 4.

### Fitting notes

- 1) Four off each M4, M5, M6, M8 studs, nuts and washers.
- 2) Four off M6x25 domed socket and washers.
- 3) Four off M6x15 spacers.



Fixings for note 1.



Fixings for note 2.



Fixings for note 3.

**Any queries please contact our technical department: (01438) 747202.**